



## HDMI OVER TWISTED PAIR TRANSMITTER & RECEIVER



### SPECIFICATIONS

<b>INPUTS:</b>	TP-551 - 1 HDMI connector. TP-552 - 2 CAT 5 IN on RJ-45 connectors.
<b>OUTPUTS:</b>	TP-551 - 2 CAT 5 OUT on RJ-45 connectors. TP-552 - 1 HDMI connector.
<b>BANDWIDTH:</b>	Supports up to 1.65Gbps bandwidth per graphic channel.
<b>COMPLIANCE WITH HDMI STANDARD:</b>	Supports HDMI 1.2 and HDCP.
<b>POWER SOURCE:</b>	12VDC, 330mA 12VDC, 440mA.
<b>DIMENSIONS:</b>	12.1cm x 7.18cm x 2.42cm (4.76" x 2.83" x 0.95") W, D, H.
<b>WEIGHT:</b>	0.3kg (0.67lbs) approx.
<b>ACCESSORIES:</b>	Power supply.

### DESCRIPTION

The TP-551 and TP-552 are a twisted pair transmitter and receiver for HDMI signals. The TP-551 converts an HDMI signal into a twisted pair signal and the TP-552 converts the signal back into an HDMI signal.

- Maximum Data Rate - 1.65 Gbps.
- HDCP Compliant.
- HDTV Compatible.
- System Range - Up to 60 meters (200 feet). Greater distances possible depending on signal resolution and cable.
- Cable - STP (shielded twisted pair) such as CAT 5.
- Enhanced EDID (Extended Display Identification Data) - Can capture an EDID setting from a device connected to the output and store it in non-volatile memory. The user can recall this setting or a factory default EDID.
- Status LEDs - Input, output & power.
- Kramer TOOLS™3 units can be rack mounted side-by-side in a 1U rack space.